

Phonak Virto™ Paradise






Phonak Virto P is the comprehensive ITE portfolio for mild to profound hearing losses. Virto P includes four models, four power levels, and four performance levels, including a noise generator for tinnitus management. Powered by the innovative technology of the Phonak Paradise platform, Virto P hearing aids are the ideal solution for those clients that prefer a custom-made solution with best hearing performance.

For more information, visit www.phonakpro.com

A Sonova brand

PHONAK
life is on

Product description

	 Virto P-Titanium P90/P70	 Virto P-10 NW O P90/P70/P50/P30	 Virto P-312 NW O P90/P70/P50/P30	 Virto P-312 P90/P70/P50/P30
Power level				
M	•	•	•	•
P	•	•	•	•
SP	•	•	•	•
UP**				•
Hardware configuration / options / technology				
Battery size	10	10	312	312
Push button (Program / Volume)	Optional	Optional	Optional	•
EasyPhone (for acoustic phone)	Optional	•	•	
MiniControl (for program or volume change)	•	•		
Volume control (wheel)		Optional	Optional	Optional
Telecoil	Optional	Optional	Optional	
Microphone technology	Omni	Omni	Omni	Directional
IP rating (without VC)	IP68*	IP68*		
Bluetooth®				•
Binaural VoiceStream Technology				•

Colors

Faceplate colors



26
Pink



22
Cocoa



28
Brown



06
Black



26
Pink



22
Cocoa



06
Black

Titanium only:
Shell color Titanium Gray & faceplate colors

Acrylic shell colors



21
Transparent



26
Pink



22
Cocoa



28
Brown



06
Black



R
Red Transparent



B
Blue Transparent

Shell styles



Virto P-Titanium



Virto P-10 NW O



Virto P-312 NW O



Virto P-312

IIC	•	•		
CIC	•	•		
MC		•	•	
ITC		•	•	
HS		•	•	•
FS		•	•	•

Performance levels

	Premium P90	Advanced P70	Standard P50	Essential P30	Features	Premium P90	Advanced P70	Standard P50	Essential P30
AutoSense OS[™] 4.0					UltraZoom	Premium	Advanced	Standard	Essential
Speech in loud noise*	•				Dynamic Noise Cancellation	•			
Speech in car	•				Speech Enhancer	•			
Comfort in echo	•				EchoBlock	•			
Music	•	•			WindBlock	•	•		
Comfort in noise	•	•	•		SoundRelax	•	•		
Speech in noise	•	•	•	•	DuoPhone	•	•	•	
Calm situation	•	•	•	•	Roger and directional setting*	•	•	•	
Media speech + mic*	•	•	•	•	SoundRecover2	•	•	•	•
Media music + mic*	•	•	•	•	User Preference Tuning	•	•	•	•
Additional programs					WhistleBlock	•	•	•	•
Max. add. programs	4	4	4	4	NoiseBlock	•	•	•	•
Comfort in echo	•				QuickSync*	•	•	•	•
Speech in loud noise*	•	•			Acoustically Optimized Vent	•	•	•	•
Speech in 360°*	•	•			Tinnitus Balance	•	•	•	•
Speech in noise	•	•	•	•	auto Acclimatization	•	•	•	•
Calm situation	•	•	•	•	Environmental balance	•	•	•	•
Comfort in noise	•	•	•	•	RogerDirect*	•	•	•	•
Music	•	•	•	•	Fine tuning channels	20	20	16	12
Acoustic phone	•	•	•	•					
Custom program	•	•	•	•					
Streaming programs									
RogerDirect + mic*	•	•	•	•					
PartnerMic + mic*	•	•	•	•					
Phone call + mic*	•	•	•	•					

Fitting

Software	Phonak Target 7.3 or higher
Interfaces	Noahlink Wireless, programming cable, HI-PRO, HI-PRO2

* Only for Virto P-312
 ** Only available in specific countries


The Bluetooth[®] word mark and logos are registered trademarks owned by the Bluetooth SIG, Inc.
 IOS is a trademark of Cisco, Inc.
 Android is a trademark of Google, Inc.

Acoustic coupling


Power level

		M	P	SP	UP**
Maximum Power Output (dB SPL)	2 cc coupler	109	115	119	127
Maximum gain (dB)	2 cc coupler	40	50	60	70
Frequency range (Hz)	2 cc coupler	<100 - 7000	<100 - 6700	<100 - 7000	<100 - 5200
Working current (mA)	Non wireless	1.1	1.2	1.1	
	Wireless	1.7	1.8	1.7	1.7


Fitting range




For mild to moderate hearing loss, all audiometric configurations



For mild to moderately-severe hearing loss, all audiometric configurations



For moderate to severe hearing loss, all audiometric configurations



For moderate to profound hearing loss, all audiometric configurations

Wireless communication portfolio

	Virto P-Titanium P90/P70	Virto P-10 NW 0 P90/P70/P50/P30	Virto P-312 NW 0 P90/P70/P50/P30	Virto P-312 P90/P70/P50/P30
Wireless accessory				
TV Connector				•
Phonak PartnerMic				•
Phonak RemoteControl				•
Roger				
RogerDirect™				•
Apps				
myPhonak				•

For more information on Virto Paradise, please visit www.phonakpro.com/virtoparadise

For information on Roger microphones, please visit www.phonakpro.com/roger

For more information on Phonak apps, please visit www.phonakpro.com/smartapps


life is on

At Phonak, we believe that well-hearing equates to well-being and is essential to living life to the fullest. For more than 70 years, we have remained passionate about creating a world where 'life is on' for everyone. Our innovative hearing solutions are designed for people of all ages and all degrees of hearing loss, to connect socially, thrive mentally and grow emotionally.

www.phonakpro.com

027-0648-02/V1.00/2022-01/ outlook © 2022 Sonova AG All rights reserved

sonova
HEAR THE WORLD

 Sonova AG · Laubisrütistrasse 28
CH-8712 Stäfa · Switzerland

 0459